



LLL-LD0612T

120V-347V input 0-10V Dimmable Driver for
Lotus LED Lights 2" HO Gimbals



Project: _____

Location: _____

Qty: _____

Notes: _____

DESCRIPTION

120-347V Input Driver 0-10V Dimmable for Lotus LED Lights 2" HO Gimbals 5.5W
Output max 40 V DC, Constant Current 130 mA, PF > 0.95

DIMENSIONS: 3 1/2" x 2" round

COMPATIBLE FIXTURES

- [LL2G-HO](#)
- [LRG2-HO](#)
- [LSG2-HO](#)



CABLE CONNECTORS

- 2 knock-outs 7/8"
- 2 Romex quick connectors

MOUNTING

directly on joist or on FRP212 plate

ORDERING GUIDE

model # **LLL-LD0612T**

Input: White (Neutral) & Black (Hot) wires with quick connectors. Connect to 120V - 347V AC according to the Dimmer Manufacturer's Instructions.

Output: Plastic FT4 / CMR rated cable with screw-in connector. Connect to compatible Lotus LED fixture from the list above

0-10V control wires: Grey (-) and Purple (+). Connect to dimming or control system 0-10V only. DO NOT CONNECT TO LINE VOLTAGE.

If you short the Grey and Purple wires the fixture would be dimmed to zero.

Warning: This driver is UL / cUL certified to be used only with Lotus LED Lights fixtures. Connecting it to any other manufacturer's fixtures will void certification and warranty and may cause overheating and fire.

<p>Lotus LED Lights USA 250 H Street # 301, Blaine WA 98230 tel 360-200-5500 Hainesport NJ, Naples FL, Vancouver WA</p>	<p>www.LotusLEDLights.com mailing addresses warehouses</p>	<p>Lotus LED Lights CANADA 1080 Cliveden Ave # 6, Delta BC V3M 6J6 tel 604-538-3090 Delta BC & Mississauga ON</p>
--	--	--