

## Picture



Specification of 10A L connector  
(Tape to Tape)  
110501010119

## Features

- Up to **10A** current
- Fits **8 mm** and **10 mm** wide strips

## Specification

Input voltage	IP rating	Rated current	Product dimension	Under Materials	Working environment	Installation method
12VDC / 24VDC	IP20	10A	15.4mm*15.4mm*6.6mm	Heat Resistant PC +65% copper	-10°~45°	Screws

## Installation

**1**

1. Unscrew the 4 screws of the connector (A)

**2**

2. Insert the end of LED tape light (B) into the connector opening (A).  
Align the connection points (B1 & B2) to be right under the screws (A1 & A2)

**3**

3. Screw down the 2 screws (A1 & A2) until firm contact with the LED tape is secured. Do not over tight

**4**

4. Insert the other end of the tape light and repeat steps 3 & 4. Make sure polarity of both tapes match on both sides of the connector(+ with + and - with -)

**5**